

Transformer Bushings

Transformer bushing for outdoor and indoor are used as structure carrying on conductor through a partition from the transformer tank

Product No.			019-00	018-00	017-00	016-00	015-00	014-00	013-00	012-00
Transformer rating		KV/Amp.	10NI/250 Amp.	10NF/250 Amp.	10NF/630 Amp.	20NF/250 Amp.	20NF/630 Amp.	30NF/250 Amp.	30NF/630 Amp.	20NF/3150 Amp.
Dimensions	Dia. A	mm	95	135	145	145	155	145	165	190
	Dia. B	mm	100	140	150	155	165	155	175	210
	Dia. I	mm	0	0	0	150	160	150	170	200
	Dia. K	mm	0	0	0			155	160	
	Dia. C max	mm	111	111	128	111	128	111	128	187
	Dia. D max	mm	74	74	88	74	88	74	88	130
	Dia. E Min	mm	33	33	39	33	39	33	39	74
	Dia F	mm	70	70	80	70	85	70	85	125
	Dia G	mm	15±1	15±1	24.5±1	15±1	24.5±1	15±1	24.5±1	17±0.5
	T	mm	22±1	22±1	30.5±1	22±1	30.5±1	22±1	30.5±1	62±0.5
	H	mm	245	295	295	385	385	485	510	410
	H1	mm	37	50	50	55	55	55	60	55
	H2	mm	76	105	105	85	85	85	80	85
	H3	mm	42	50	70	90	90	85	85	80
H4	mm	25	25	25	50	50	90	90	60	
H5	mm	65	65	65	25	25	65	70	30	
H6	mm	0	0	0	80	80	25	25	100	
H7	mm	0	0	0			80	100		
Visible discharge voltage		KV	12	12	12	12	12	12	12	12
Power frequency	Dry	KV	45	45	45	45	45	45	45	45
One minuite withstand voltage	Wet	KV	45	45	45	45	45	45	45	45
Impulse withstand voltage		KV	95	95	95	95	95	95	95	95
Net weight (Approx.)		KV	2.7	3.8	4.9	5.9	6.8	7.6	9.6	6

* Due to continuous product improvements, some specifications could be changed without notice

* Other designs are available

